

浮動(非固定IP)網路設定使用說明 DF系列

【網路設定操作說明】

1. 電腦 IE 瀏覽器輸入網址 www.hik-connect.com，點擊註冊 Register

User Register

* User Name:

* Password:


* Confirm Password:

* Country:

* Email:

Country Code:

Mobile Phone Number:

* Verification Code: 

I Agree [Service Agreement](#)

Next

2. 註冊成功後將會進入帳號主頁

Device Management Search by Device Serial No.

Device Domain	Device Serial No.	IP/Port No.	Status	Device Operation
No device.				

My Shared Devices

My Account

3. 確認網路已設定完成後，啟用 系統設定>網路設定>平台連接，輸入驗證碼

設定

常用 平台連接 PPPOE DDNS NTP 電子郵件設定 埠映射 進階設定

啟動

連接類型 **Guarding Vision**

伺服器位址 自訂

啟用碼流加密

驗證碼

狀態 **離線**



4.新增設備

 Add

Add Device

Device Serial No.:

設備資訊	攝影機資訊	錄影資訊	警報資訊	網路資訊	硬碟資訊
設備名稱	Embedded Net DVR				
型號	DS-7204HGHI-SH				
序號	0420151223AAWR563727512WCVU				
韌體版本	V3.3.2, Build 151229				
驗證碼	ZZZZZ				

(序號通常會在主機上有 9 碼數字或在主機系統維護內)

5.若輸入的序號正確，該設備就會在下方視窗自動顯示出來。

Add Device

Device Serial No.:



DS-7204HGHI-SH(563727512)

6.輸入(步驟2)主機驗證碼

Add Device

Device Serial No.:

Verification Code:

7.連線成功

Device Management

Device Serial No. Search by Device Serial No.   Add

Device Domain	Device Serial No.	IP/Port No.	Status	Device Operation
563727512	563727512	114.42.32.187	Online	  

8.於網頁中輸入<https://isgp.hik-connect.com/>加上主機序號即可連線
(以圖為例<https://isgp.hik-connect.com/563727512>)



The image shows a login form with two input fields and a button. The first field is labeled '帳號' (Account) and the second is labeled '密碼' (Password). Below the fields is a red button labeled '登入' (Login).

(輸入主機帳號、密碼後即可登入，帳號:admin、預設密碼:se888888)